

RUT361 LEDs

[Main Page](#) > [RUT Routers](#) > [RUT361](#) > [RUT361 Manual](#) > **RUT361 LEDs**

This page contains information the different types of LEDs and their behaviour on a RUT361 device.



Contents

- [1 Power LED](#)
- [2 Ethernet port LEDs](#)
- [3 Mobile network type LEDs](#)
- [4 Mobile signal strength indication LEDs](#)

Power LED

The **power LED** is located on the bottom left corner of the front panel, just under the power connector.



It indicates whether the device is powered on or not.

	State	Description
LED turned on		Device is powered on.
LED turned off		Device is not powered on.

Ethernet port LEDs

The **Ethernet port LEDs** are located on the device's front panel, under each respective Ethernet port.



	State	Description
LED on		Operating as a 10/100 Mbps connection.
LED off		No link established.
LED blinking		Connection established and there is activity on this port (data being transferred).

Mobile network type LEDs

The **mobile network type LEDs** are located near the SIM card slot.



They display which type of Internet connection is currently active.

Action	Description
--------	-------------

3G LED turned on
4G LED turned on
3G blinking
4G blinking
All LEDs blinking at the same time every 500 ms
All LEDs turn on and off in a sequence one after the other

Device is connected to a 3G network.
Device is connected to a 4G network.
Device is connected to a 3G network but hasn't received an IP address.
Device is connected to a 4G network but hasn't received an IP address.
No SIM card or incorrect PIN.
The device is attempting to connect to a mobile network operator.

Mobile signal strength indication LEDs

The **mobile signal strength indication LEDs** are located near the SIM card slot.



The number of lit up LEDs represents a different mobile signal strength ([RSSI](#)) value in dBm.

No. of lit up LEDs	Signal strength value
0	≤ -111 dBm
1	-110 dBm to -82 dBm
2	-81 dBm to -52 dBm
3	≥ -51 dBm

The Mobile signal strength LEDs can also be used as a **time indicator for holding the reset button**. When you press and hold the reset button, if there is a User's default configuration configured on the device, you have to hold it pressed for 6 seconds (by default) to initiate a **User's default configuration reset** and 12 seconds (by default) to initiate a **Factory reset**. Otherwise, it is only necessary to hold the reset button for 6 seconds to trigger a **Factory reset**. If the button was held down longer than 20 seconds (by default) no action will be taken.

While holding the reset button each lit up signal strength LED indicate that a period of two seconds has passed. In case with **RUT361**, when all 3 Mobile signal strength LEDs are lit up, they represent that 6 (LED number multiplied by 2) seconds have passed since you pressed down on the reset button.

After releasing the button at one of the reset periods, all 3 LEDs will start blinking every 1 second. This signifies that the router **has begun the reset**.