

RUT955 Profiles

[Main Page](#) > [RUT Routers](#) > [RUT955](#) > [RUT955 Manual](#) > [RUT955 WebUI](#) > [RUT955 System section](#) > **RUT955 Profiles**

The information in this page is updated in accordance with firmware version [RUT9_R_00.07.04.5](#).

Note: [click here](#) for the old style WebUI (FW version RUT9XX_R_00.06.09.5 and earlier) user manual page.

Contents

- [1 Summary](#)
- [2 Configuration Profiles](#)
- [3 Scheduler](#)
 - [3.1 General Configuration](#)
 - [3.2 Profile Scheduler Instances](#)
 - [3.2.1 Profile Scheduler Instance Configuration](#)
 - [3.2.2 Profile Scheduler Instance Example](#)

Summary

Configuration **profiles** provide a way to create multiple distinct device configuration sets and apply them to the device based on current user requirements. This chapter is an overview of the Profiles page in RUT955 devices.

Configuration Profiles

This section displays user defined **configuration profiles**:

∨ CONFIGURATION PROFILES

PROFILE NAME	CREATED / UPDATED
default	12/03/2020 14:32

∧ ADD NEW PROFILE

NAME	PROFILE FROM CURRENT CONFIGURATION
<input type="text"/>	<input checked="" type="checkbox"/>

off on

ADD

SAVE & APPLY

To create a new profile, configure the device in accordance with your needs, go to this page, enter a

custom name for the profile and click the 'Add' button. You can also choose to create a profile without any previous configurations. A new profile with the given name will appear in the "configuration profiles" list:

Configuration Profiles interface showing a list of profiles and an 'Add New Profile' form.

PROFILE NAME	CREATED / UPDATED	
default	08/21/2020 07:35	
Demo	08/21/2020 06:04	APPLY X

ADD NEW PROFILE

NAME: Demo

PROFILE FROM CURRENT CONFIGURATION: off on

Buttons: ADD, SAVE & APPLY, APPLY

The 'Apply' button applies the adjacent configuration on the device.

Scheduler

The **Profile Scheduler** provides a possibility to set up a schedule of when the device should use one profile configuration or another.

Check [Profile Scheduler Instance Example](#) to get a better understanding at how Profile Scheduler Instances works.

General Configuration

The **General Configuration** section is used to enable the Scheduler itself. Created instances won't work unless this option is turned on.

GENERAL CONFIGURATION



Enable Scheduler

Profile Scheduler Instances

The **Profile Scheduler Instances** section allows you to create profile Instances to be enabled during specific time intervals. To add a new Instance click **Add** button.

Note: new Instance can only be created if there is at least one custom [profile](#) created.

^ PROFILE SCHEDULER INSTANCES

PROFILE	TYPE	FROM	TO		
example	Weekdays	Every Monday, 12:00	Every Tuesday, 12:00	 	<input type="checkbox"/> off <input type="checkbox"/> on

[ADD](#)

[SAVE & APPLY](#)

Profile Scheduler Instance Configuration

This page is used to configure profile, time and day of selected scheduler instance. Refer to the figure and table below for information on the Profile Scheduler Instance Configuration fields:

^ PROFILE SCHEDULER INSTANCE CONFIGURATION

Enable off on

Profile

Interval Type

Start Day

Start Time

End Day

End Time

[SAVE & APPLY](#)

Field	Value	Description
Enable	off on; default: off	Enable selected instance for scheduler.
Profile	profiles; default: none	Select profile which will be applied during specified time interval.
Interval Type	Weekdays Month Days; default: Weekdays	Depending on your needs select whether you want to configure weekdays or specific month days.
Start Time	time; default: 12:00	Enter time of the start of interval in which scheduler will switch profiles.
End Time	time; default: 12:00	Enter time of the end of interval in which scheduler will switch profiles back.
Interval Type: Weekdays		
Start Day	Weekday [Monday..Sunday]; default: Sunday	Select a day of the start of interval in which scheduler will switch profiles.
End Day	Weekday [Monday..Sunday]; default: Sunday	Select a day of the end of interval in which scheduler will switch profiles back.
Interval Type: Month Days		
Start Day	Day of month [1..31]; default: 1	Select a day of the start of interval in which scheduler will switch profiles.

End Day	Day of month [1..31]; default: 1	Select a day of the end of interval in which scheduler will switch profiles back.
Force last day	off on; default: off	Force intervals to accept last day of month as valid option if selected day doesn't exist in ongoing month.

Profile Scheduler Instance Example

Scheduler will use *profile instance* if it is enabled **and** it's time interval matches device's [date](#), otherwise *default* profile will be used.

Example - we have 3 profiles in total:

- default
- Profile A
- Profile B

We create profile instances for Profiles A and B:

- Profile A: 08:00 - 11:00
- Profile B: 13:00 - 20:00

During 11:00 - 13:00 and 20:00 - 08:00 *default* profile will be used.