

## Status Control Commands

[illegible]☐

# Contents

- 1 Status Control Commands

- [1.1 AT+CPAS Mobile Equipment Activity Status](#)
- [1.2 AT+CEER Extended Error Report](#)
- [1.3 AT+QCFG Extended Configuration Settings](#)
- [1.4 AT+QCFG="gprsattach" GPRS Attach Mode Configuration](#)
- [1.5 AT+QCFG="nwscanmode" Network Search Mode Configuration](#)
- [1.6 AT+QCFG="nwscanseq" Network Searching Sequence Configuration](#)
- [1.7 AT+QCFG="roamservice" Roam Service Configuration](#)
- [1.8 AT+QCFG="servicedomain" Service Domain Configuration](#)
- [1.9 AT+QCFG="band" Band Configuration](#)
- [1.10 AT+QCFG="hsdpacat" HSDPA Category Configuration](#)
- [1.11 AT+QCFG="hsupacat" HSUPA Category Configuration](#)
- [1.12 AT+QCFG="rrc" RRC Release Version Configuration](#)
- [1.13 AT+QCFG="sgsn" UE SGSN Release Version Configuration](#)
- [1.14 AT+QCFG="msc" UE MSC Release Version Configuration](#)
- [1.15 AT+QCFG="PDP/duplicatechk" Establish Multi PDNs with the Same APN](#)
- [1.16 AT+QCFG="urc/ri/ring" RI Behavior When RING URC is Presented](#)
- [1.17 AT+QCFG="urc/ri/smsincoming" RIBehavior WhenIncoming SMSURCs are Presented](#)
- [1.18 AT+QCFG="urc/ri/other" RI Behavior When Other URCsare Presented](#)
- [1.19 AT+QCFG="risignaltype" RISignal Output Carrier](#)
- [1.20 AT+QCFG="urc/delay"Delay URC Indication](#)
- [1.21 AT+QCFG="urc/cache"URC Cache Function](#)
- [1.22 AT+QCFG="tone/incoming"Ring tone Function](#)
- [1.23 AT+QINDCFG URC Indication Configuration](#)

## Status Control Commands

## AT+CPAS Mobile Equipment Activity Status

The `ExecutionCommand` queries the module's activity status.

## AT+CEER Extended Error Report

The command is used to query an extended error and report the cause of the last failed operation, such as:

- the failure to release a call;
- the failure to set up a call (both mobile originated or terminated);
- the failure to modify a call by using supplementary services;
- the failure to activate, register, query, deactivate or deregister a supplementary service;
- the failure to attach GPRS or the failure to activate a PDP context;
- the failure to detach GPRS or the failure to deactivate a PDP context.

The release cause **<text>** is a text to describe the cause information given by the network.

## **AT+QCFG Extended Configuration Settings**

---

The command is used to query and configure various settings of UE.

### **AT+QCFG="gprsattach" GPRS Attach Mode Configuration**

---

The command specifies the mode to attach GPRS when UE is powered on. This configuration is valid only after the module is restarted.

### **AT+QCFG="nwscanmode" Network Search Mode Configuration**

---

The command specifies the network mode to be searched. If **<effect>** is omitted, the configuration will take effect immediately.

### **AT+QCFG="nwscanseq" Network Searching Sequence Configuration**

---

The command specifies the sequence of searching network. This configuration is valid only after the module is restarted.

### **AT+QCFG="roamservice" Roam Service Configuration**

---

The command is used to enable or disable the roam service. If **<effect>** is omitted, the configuration will take effect immediately.

### **AT+QCFG="servicedomain" Service Domain Configuration**

---

The command specifies the registered service domain. If **<effect>** is omitted, the configuration will take effect immediately.

## **AT+QCFG="band" Band Configuration**

---

The command specifies the preferred frequency bands to be searched of UE. If **<effect>** is omitted, the configuration will take effect immediately.

## **AT+QCFG="hsdpacat" HSDPA Category Configuration**

---

The command specifies the HSDPA category. This configuration is valid only after the module is restarted.

## **AT+QCFG="hsupacat" HSUPA Category Configuration**

---

The command specifies the HSUPA category. This configuration is valid only after the module is restarted.

## **AT+QCFG="rrc" RRC Release Version Configuration**

---

The command specifies the RRC release version. This configuration is valid only after the module is restarted.

## **AT+QCFG="sgsn" UE SGSN Release Version Configuration**

---

The command specifies the UE SGSN release version. This configuration is valid only after the module is restarted.

## **AT+QCFG="msc" UE MSC Release Version Configuration**

---

The command specifies the UE MSC release version. This configuration is valid only after the module is restarted.

## **AT+QCFG="PDP/duplicatechk" Establish Multi PDNs with the Same APN**

---

The command allows/refuses establishing multi PDNs with the same APN profile. The configuration will take effect immediately.

## **AT+QCFG="urc/ri/ring" RI Behavior When RING URC is Presented**

---

**AT+QCFG="urc/ri/ring", AT+QCFG="urc/ri/smsincoming" and AT+QCFG="urc/ri/other"** control the RI (ring indicator) behavior when a URC is reported. These configurations will be stored into NV automatically. The ring indicator is active low.  
**AT+QCFG="urc/ri/ring"** specifies the RI behavior when URC **RING** is presented to indicate an incoming call.

The sum of parameter **<activeduration>** and **<inactiveduration>** determines the interval time of "RING" indications when a call is coming.

### **AT+QCFG="urc/ri/smsincoming" RIBehavior WhenIncoming SMSURCs are Presented**

---

The command specifies the RI (ring indicator) behavior when related incoming message URCs are presented. Related incoming message URCs list: **+CMTI,+CMT,+CDS** and **+CBM**.

### **AT+QCFG="urc/ri/other" RI Behavior When Other URCsare Presented**

---

The command specifies the RI (ring indicator)behavior when other URCs are presented.

### **AT+QCFG="risignaltype" RISignal Output Carrier**

---

The command specifies the RI (ring indicator) signal output carrier.

### **AT+QCFG="urc/delay"Delay URC Indication**

---

The commandcan delay the output ofURC indication until ring indicatorpulse ends.

### **AT+QCFG="urc/cache"URC Cache Function**

---

### **AT+QCFG="tone/incoming"Ring tone Function**

---

### **AT+QINDCFG URC Indication Configuration**

---

The command is used to control URC indication.