

RUT955 Profiles (legacy WebUI)

[Main Page](#) > [RUT Routers](#) > [RUT955](#) > [RUT955 Manual](#) > [RUT955 Legacy WebUI](#) > [RUT955 System section \(legacy\)](#) > **RUT955 Profiles (legacy WebUI)**

The information in this page is updated in accordance with firmware version [RUT9XX_R_00.06.09.5](#).

Note: this user manual page is for RUT955's old WebUI style available in earlier FW versions. [Click here](#) for information based on the latest FW version.

Contents

- [1 Summary](#)
- [2 General](#)
- [3 Scheduler](#)

Summary

Profiles provides a way to create multiple distinct router configuration sets and apply them to the router based on current user requirements.

This chapter of the user manual provides an overview of the Profiles page for RUT955 devices.

General

This section displays user defined **profiles** and provides the possibility to add new ones. To create a new profile, enter a custom name for the profile and click the **Add** button.

You can click on the checkbox to create new profile from your current configuration, otherwise new profile will have factory default settings, only the password of the router will be transferred to the new configuration.

Note: Profiles can be switched with [SMS Utilities](#), [Input/Output](#) functions or via this page.

Scheduler

The **Profile Scheduler** provides a possibility to set up a schedule of when the router should use one configuration or another. Different configuration profiles use differently colored dots for distinction. Select a profile from the dropdown below and click on time interval boxes in the scheduler table to indicate on which days/hours the profile should be applied.