

Template:Networking rut240 manual supported frequency bands table

Product code	Region (operator)	Supported bands
RUT240 *0****	Europe ² , the Middle East, Africa, Korea, Thailand, India, Malaysia	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz)• 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz)• 3G: B1 (2100 MHz), B5 (850 MHz), B8 (900 MHz)• 2G: B3 (1800 MHz), B8 (900 MHz)
RUT240 *1****	North America (AT&T, Bell, T-Mobile) ¹	<ul style="list-style-type: none">• 4G (LTE-FDD): B2 (1900 MHz), B4 (1700 MHz), B12 (700 MHz)• 3G: B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz)
RUT240 *2****	North America (Verizon)	<ul style="list-style-type: none">• 4G (LTE-FDD): B4 (1700 MHz), B13 (700 MHz)
RUT240 *4****	South America, Australia, New Zealand, Taiwan	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B28 (700 MHz)• 4G (LTE-TDD): B40 (2300 MHz)• 3G: B1 (2100 MHz), B2 (1900 MHz), B5 (850 MHz), B8 (900 MHz)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
RUT240 *5****	Japan	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B8 (900 MHz), B18 (850 MHz), B19 (800 MHz), B26 (850 MHz)• 4G (LTE-TDD): B41 (2500 MHz)• 3G: B1 (2100 MHz), B6 (800 MHz), B8 (900 MHz), B19 (800 MHz)
RUT240 *6****	Europe ² , the Middle East, Africa, Korea, Thailand, Malaysia	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28A (700 MHz)• 3G: B1 (2100 MHz), B8 (900 MHz)• 2G: B3 (1800 MHz), B8 (900 MHz)
RUT240 *7****	Global ²	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B12 (700 MHz), B13 (1800 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B26 (850 MHz), B28 (700 MHz)• 4G (LTE-TDD): B38 (2600 MHz), B39 (1900 MHz), B40 (2300 MHz), B41 (2500 MHz)• 3G: B1 (2100 MHz), B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz), B6 (800 MHz), B8 (900 MHz), B19 (800 MHz)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
RUT240 *8****	Europe ² , the Middle East, Africa, Korea, Thailand, India, Malaysia	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28A (700 MHz)• 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz)• 3G: B1 (2100 MHz), B8 (900 MHz)• 2G: B3 (1800 MHz), B8 (900 MHz)
RUT240 *D****	Europe ² , the Middle East, Africa	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz)• 4G (LTE-TDD): B40 (2300 MHz)• 3G: B1 (2100 MHz), B5 (850 MHz), B8 (900 MHz)• 2G: B3 (1800 MHz), B8 (900 MHz)
RUT240 *0*00G	Europe ² , the Middle East, Africa, Korea, Thailand, India (Vodafone)	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz)• 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz)• 3G: B1 (2100 MHz), B5 (850 MHz), B8 (900 MHz)• 2G: B3 (1800 MHz), B8 (900 MHz)

¹ Router is not certified on T-Mobile, Bell network (In progress).

² Regional availability - excluding Russia & Belarus.