https://wiki.teltonika-networks.com/view/Template:Networking\_rutm08\_manual\_power\_consumption \_table

## Template:Networking rutm08 manual power consumption table

|  | Test type | Current (mA) | Power consumption<br>(W) |
|--|-----------|--------------|--------------------------|
| Idle (9 V)   |           | 117          | 1.06                     |
| Idle (12 V)  |           | 87           | 1.05                     |
| Idle (24 V)  |           | 42           | 1.02                     |
|  | Test type | Current (mA) | Power consumption<br>(W) |
| 2 LAN devices connected <sup>1</sup> (9 V)   |           | 186          | 1.68                     |
| 2 LAN devices connected <sup>1</sup> (12 V)  |           | 139          | 1.68                     |
| 2 LAN devices connected $^{1}$ (24 V)  |           | 67           | 1.62                     |
|  | Test type | Current (mA) | Power consumption<br>(W) |
| 4 LAN devices connected <sup>1</sup> + high CPU load <sup>2</sup> + USB device connected <sup>3</sup> (9 V)  |           | 578          | 5.19                     |
| 4 LAN devices connected <sup>1</sup> + high CPU load <sup>2</sup> + USB device connected <sup>3</sup> (12 V) |           | 426          | 5.12                     |

215

5.15

4 LAN devices connected <sup>1</sup> + high CPU load <sup>2</sup> + USB device connected <sup>3</sup> (24 V)

<sup>1</sup> - Data streams between RUTM08 and other connected LAN devices created using iPerf.

<sup>2</sup> - Load created using *md5sum* (calculation and verification of 128-bit MD5 hashes).

 $^{\scriptscriptstyle 3}$  - USB device with ~ 500 mA current draw.

Power consumption may differ due to mobile data transmission speed, testing environment and conditions.