

# Template:Networking rutxr1 manual supported frequency bands table

Product code	Region (operator)	Supported bands
RUTXR1 0****	Europe, the Middle East, Africa, Australia, APAC <sup>2</sup> , Brazil, Malaysia	<ul style="list-style-type: none"><li>• <b>4G (LTE-FDD)</b>: B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz), B32<sup>1</sup> (1500 MHz)</li><li>• <b>4G (LTE-TDD)</b>: B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz)</li><li>• <b>3G</b>: B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)</li></ul>
RUTXR1 1****	North America	<ul style="list-style-type: none"><li>• <b>4G (LTE-FDD)</b>: B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B12 (700 MHz), B13 (700 MHz), B25 (1900 MHz), B26 (850 MHz), B29<sup>1</sup> (700 MHz), B30 (2300 MHz), B66 (1700/2100 MHz)</li><li>• <b>3G</b>: B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz)</li></ul>

<sup>1</sup> LTE-FDD B29 and B32 Support Rx Only, and in 2×CA it is Only for Secondary Component Carrier.

<sup>2</sup> Excluding Japan and CMCC.