

# RUT301 OPC UA Server

[Main Page](#) > [RUT Routers](#) > [RUT301](#) > [RUT301 Manual](#) > [RUT301 WebUI](#) > [RUT301 Services section](#) > **RUT301 OPC UA Server**

The information in this page is updated in accordance with firmware version [RUT301\\_R\\_00.07.07.3](#).

□

## Contents

- [1 Summary](#)
- [2 OPC UA Server Configuration](#)
- [3 OPC UA Server variables](#)

## Summary

OPC Unified Architecture (**OPC UA**) is a cross-platform, open-source, IEC62541 standard for data exchange from sensors to cloud applications developed by the OPC Foundation. The *UA* in OPC UA stands for “Unified Architecture” and refers to the latest specification of the standard. It differs from its predecessor in that it is platform-independent, moving away from COM/DCOM to purely binary TCP/IP or alternatively SOAP.

---

This manual page provides an overview of the OPC UA Server in RUT301 devices.

**Note:** OPC UA Server is additional software that can be installed from the **System** → [Package Manager](#) page.

## OPC UA Server Configuration

The **OPC UA Server Configuration** section is used to enable the local OPC UA server.

✖

Field	Value	Description
Enable	off   on; default: <b>off</b>	Enables OPC UA server.
Port	integer [1..65535]; default: <b>none</b>	Service port.

## OPC UA Server variables

All **RUTOS** device variables are described in the table below:

**Note:** All the variables have these qualities in common:

- Namespace index is 1
- Node ID type is string
- Read-only
- Updated upon request

	<b>ID</b>	<b>Type</b>	<b>Description</b>
sys_uptime		UINT32	System uptime in seconds.
sys_serial		String	Device serial number.
sys_devname		String	Device name.
sys_devcode		String	Device code.
sys_version		String	Firmware version.
sys_hostname		String	Hostname.
lan_mac		String	LAN MAC address.
lan_ip		String	IP address of LAN interface.
lan_mask		String	Subnet mask of LAN interface.
lan_gateway		String	Gateway IP address of LAN interface.
lan_dns		Array of String	IP addresses of LAN interface DNS servers.
wan_ip		Array of String	IP address of WAN interface.
io_dio_dir		Array of BOOL	Directions of digital input/output pins. 0=IN, 1=OUT.
io_dio		Array of BOOL	Values of digital input/output pins.