

RUT955 Dynamic DNS

[Main Page](#) > [RUT Routers](#) > [RUT955](#) > [RUT955 Manual](#) > [RUT955 WebUI](#) > [RUT955 Services section](#) > **RUT955 Dynamic DNS**

The information in this page is updated in accordance with firmware version [RUT9_R_00.07.06.10](#).

Note: [click here](#) for the old style WebUI (FW version RUT9XX_R_00.06.09.5 and earlier) user manual page.



Contents

- [1 Summary](#)
- [2 Dynamic DNS Overview](#)
- [3 Editing a DDNS instance](#)
 - [3.1 cloudflare.com](#)
- [4 See also](#)

Summary

Dynamic DNS (DDNS or DynDNS) is a method of automatically updating a name server in the Domain Name System (DNS). This is most often utilized when the end user has a [dynamic IP address](#) and wants to bind it to a static hostname.

The device is compatible with many different third party DNS services that provide the possibility to create a custom hostname and bind it to an IP address. The DDNS service periodically updates the IP address information of the hostname, making sure that the device remains reachable via the same hostname even in cases when its IP address has changed.

This chapter is an overview of the Dynamic DNS section for RUT955 devices.

Note: Dynamic DNS is additional software that can be installed from the **System** → [Package Manager](#) page.

Dynamic DNS Overview

By default, an unconfigured DDNS instance will be present in the **Dynamic DNS Overview** page (the figure below is an example of this). You can create more DDNS instances by entering a name and clicking the "Add" button or you can edit the existing instance since it is not operational by default.



Editing a DDNS instance

To configure a DDNS instance, click the "**Edit**" button located next to it.

The figure below is an example of the edit page of the default DDNS instance called "MyDDNS" (already present in the device by default) and the table below provides information on the configuration fields contained in that page:



Field	Value	Description
Enabled	off on; Default: off	Turns the DDNS instance on or off.
Lookup hostname	host; Default: yourhost.example.com	Fully qualified domain name (FQDN) of your defined host. This is required to verify what the hostname's current IP address at DNS is (using <i>nslookup/host</i> command).
DDNS service provider	third party DNS service (chosen from list*) -- custom --; Default: dyn.com	Third party DNS service provider.
Domain	host; Default: yourhost.example.com	Hostname that will be linked with the device IP address.
Username	string; Default: your_username	User name required to login to the third party DNS service; used to periodically login to your DNS service account and make necessary updates.
Password	string; Default: your_password	Password required to login to the third party DNS service; used to periodically login to your DNS service account and make necessary updates.
IP address source	Custom Public Private Script; Default: Custom	Defines the source to read the system's IPv4-Address from, that will be sent to the DNS provider. For example, if your device has a Private IP (i.e., 10.140.56.57) on its WAN interface, then you can send this exact IP to DDNS server by selecting <i>Private</i> .
Network	network interface; Default: lan	Specifies which interface's IP address should be bound to the hostname
Check Interval	integer [5..3600]; Default: 10 integer [300..3600]* integer [1..3600]**	Frequency at which the device will check whether it's IP address has changed. The minimal amount of time that can be specified is 5 minutes or 300 seconds. *If selected interval is Seconds. **If selected interval is Hours.
Force Interval	integer [5..3600]; Default: 10 integer [1..3600]*	Frequency at which IP update requests are sent to the DNS provider. The minimal amount of time that can be specified is 5 minutes and not less than Check Interval . *If selected interval is Hours or Days.

Azure IoT Hub

DMVPN

MODBUS TCP Master

OSPF Daemon

SNMP

TCPdump

UPNP

BGP Daemon

DNP3

MODBUS TCP Slave

QoS

Speedtest

ThingWorx

VRRP

Cloud of Things

EIGRP Daemon

MODBUS MQTT Gateway

Relay Configuration

SQM

Tinc VPN

Wake on LAN

Cumulocity

Hotspot

MQTT

Relay Configuration

SSHFS

TR-069

Wifi Scanner

Data to Server

Hotspot Themes

NHRP Daemon

RIP Daemon

SSTP

Traffic Logging

ZeroTier

Dynamic DNS

Language - German

NTPD

SMPP

Stunnel

UDP Broadcast Relay

cloudflare.com

Note: To use subdomains with **Cloudflare** services, you must use the @ symbol.

service_name	cloudflare.com-v4
domain	[Your domain, here: example.com]
username	Bearer
password	[Your API token]

To use subdomains (CNAME or A records), use the format below when filling your credentials:

domain	{subdomain}@[zone]
--------	--------------------

Examples:

If the hostname is "sample.example.com", the "domain" field would be "sample@example.com"

If the hostname is "dev1.sample.example.com", the "domain" field would be "dev1.sample@example.com"

If using Cloudflare's "Subdomain Support", your zone may already be "foo.example.com", so if the DDNS hostname is "bar.foo.example.com" the domain field would be "bar@foo.example.com"

See also

- Dynamic DNS configuration examples for specific providers:
 - noip.com
 - dnsdynamic.org
 - dynu.com
 - dyn.com