

RUTX10 NTP

[Main Page](#) > [RUTX Routers](#) > [RUTX10](#) > [RUTX10 Manual](#) > [RUTX10 WebUI](#) > [RUTX10 Services section](#) > **RUTX10 NTP**

The information in this page is updated in accordance with firmware version [RUTX_R_00.07.04.5](#).

□

Contents

- [1 Summary](#)
- [2 General](#)
- [3 NTP](#)
 - [3.1 Time Synchronization](#)
 - [3.2 NTP Server](#)
- [4 NTPD](#)

Summary

Network Time Protocol (NTP) is a networking protocol for clock synchronization between computer systems over packet-switched, variable-latency data networks. This chapter is an overview of the NTP section for RUTX10 devices.

General

The **Time Synchronization** section lets you select time zone and synchronize the time.

The figure below is an example of the Time Synchronization section and the table below provides information about the fields contained in that section:

∨ TIME SYNCHRONISATION

Current system time 6/12/2021, 1:57:20 PM

[SYNC WITH BROWSER](#)

Time zone

[SAVE & APPLY](#)

Field	Value	Description
Current system time	time; default: none	Current local time of the device.
Sync with browser	-(interactive button)	Click to synchronize device time and time zone to browsers, if your device time or time zone is not correct.

Time zone time zone; default: **UTC** The device will sync time in accordance with the selected time zone.

NTP

This section is used to configure NTP client, server and time servers.

Time Synchronization

▼ NTP CLIENT

Enable NTP client off on

Save time to flash off on

Force servers off on

Update interval (in seconds)

Offset frequency

Count of time synchronizations

HOSTNAME

<input type="text" value="0.openwrt.pool.ntp.org"/>	<input type="button" value="X"/>
<input type="text" value="1.openwrt.pool.ntp.org"/>	<input type="button" value="X"/>
<input type="text" value="2.openwrt.pool.ntp.org"/>	<input type="button" value="X"/>
<input type="text" value="3.openwrt.pool.ntp.org"/>	<input type="button" value="X"/>
<input type="button" value="ADD"/>	

Field	Value	Description
Enable NTP Client	off on; default: on	Turns NTP on or off.
Save time to flash	off on; default: off	Saves last synchronized time to flash memory.
Force Servers	off on; default: off	Forces unreliable NTP servers.
Update interval (in seconds)	integer; default: 86400	How often the device will update the time.
Offset frequency	integer; default: 0	Adjusts the minor drift of the clock so that it will run more accurately.
Count of time synchronizations	integer; default: none	The amount of times the device will perform time synchronizations. Leave empty in order to set to infinite.
Hostname	ip url; default: 0.openwrt.pool.ntp.org	NTP servers that this device uses to sync time.

NTP Server

The device can also act as an **NTP Server**, providing clock synchronization to other devices in the

network. From this section you can turn this feature on or off:

^ NTP SERVER

Enable NTP Server

SAVE & APPLY

NTPD

The **NTPD** program is an operating system daemon that synchronizes the system clock to remote NTP time servers or local reference clocks. NTPD includes the ability to use this to keep your clock in sync and will run more accurately than a clock on a device not running NTPD. NTPD will also use several servers to improve accuracy. It is a complete implementation of NTP version 4 defined by RFC-5905, but also retains compatible with version 3 defined by RFC-1305 and versions 1 and 2, defined by RFC-1059 and RFC-1119, respectively.

∨ NTPD

Enable

Enable NTP config from file

NTP configuration file [BROWSE](#)

Server

Enable Server

SAVE & APPLY

Field	Value	Description
Enable NTPD	off on; default: off	Turns NTPD on or off.
Enable NTP config from file	off on; default: off	Run NTPD with uploaded configuration file.
NTP configuration file	.conf file; default: none	Upload a custom configuration file.
Server	ip url; default: 0.openwrt.pool.ntp.org	NTP servers that this device uses to sync time.
Enable Server	off on; default: off	Enables NTPD server to make the router act as an NTP server so that it can provide time synchronization services for other network devices.