

TRB142 Power Consumption

[Main Page](#) > [TRB Gateways](#) > [TRB142](#) > [TRB142 Manual](#) > **TRB142 Power Consumption**

[TRB142](#) power consumption values in different states of operation are represented in the table(s) below:

Test type	Current (mA)	Power consumption (W)
Idle, no SIM card inserted (9 V)	34	0.31
Idle, no SIM card inserted (12 V)	27	0.32
Idle, no SIM card inserted (24 V)	14	0.34

Test type	Current (mA)	Power consumption (W)
Idle + mobile data on ¹ (9 V)	49	0.44
Idle + mobile data on ¹ (12 V)	36	0.44
Idle + mobile data on ¹ (24 V)	21	0.50

Test type	Current (mA)	Power consumption (W)
Mobile data on ¹ + 1 LAN device connected ² (9 V)	60	0.54
Mobile data on ¹ + 1 LAN device connected ² (12 V)	46	0.55
Mobile data on ¹ + 1 LAN device connected ² (24 V)	27	0.65

Test type	Current (mA)	Power consumption (W)
Max speed LTE transmission + 1 LAN device connected ² + high CPU load ³ + device connected to RS232 (9 V)	340	3.06
Max speed LTE transmission + 1 LAN device connected ² + high CPU load ³ + device connected to RS232 (12 V)	249	2.99
Max speed LTE transmission + 1 LAN device connected ² + high CPU load ³ + device connected to RS232 (24 V)	143	3.43

¹ - Only mobile data connection established with no additional traffic.

² - Data streams between TRB142 and other connected LAN devices created using iPerf.

³ - Load created using *md5sum* (calculation and verification of 128-bit MD5 hashes).

Power consumption may differ due to mobile data transmission speed, testing environment and conditions.