

Template:Networking rut manual iot platforms legacy

The information in this page is updated in accordance with firmware version .



Contents

- [1 Summary](#)
- [2 Azure IoT Hub](#)
 - [2.1 GSM values](#)
 - [2.2 MQTT messages](#)
- [3 Cumulocity](#)
- [4 Cloud of Things](#)
- [5 ThingWorx](#)

Summary

The **IoT Platforms** section is used to configure various cloud solutions used for remote control of this device.

This chapter of the user manual provides an overview of the Cloud Solutions page for {{{name}}} devices.

Azure IoT Hub

Azure IoT Hub is a set of cloud services by Microsoft's designed to help an organization meet various business challenges related to remote device monitoring.

Monitoring can be configured in two different ways:

- **GSM Values** - the device periodically sends information on selected mobile connection parameters.
- **MQTT messages** - the device connects to an MQTT broker and subscribes to a specified topic.

More information on *Message Types* in the sections below.

GSM values



Field	Value	Description
-------	-------	-------------

Enable Azure IoT Hub monitoring	yes no; default: no	Turns the Azure IoT Hub service on or off.
Connection string	string; default: none	Unique connection string a.k.a. server address provided by the Azure Iot Hub service.
Message sending interval (sec.)	integer [10..99999]; default: 300	data sending frequency in seconds.
GSM Values	IP Address Number of bytes sent Number of bytes received Mobile connection state Network link state IMEI ICCID Model Manufacturer Serial Revision IMSI SIM state PIN state GSM signal WCDMA RSCP WCDMA EC/IO Cell ID Operator Operator number Connection type Temperature PIN count; default: none	Selects the mobile connection parameter values that should be sent to the Azure IoT Hub service.

MQTT messages

✖

Field	Value	Description
Enable Azure IoT Hub monitoring	yes no; default: no	Turns the Azure IoT Hub service on or off.
Connection string	string; default: none	Unique connection string a.k.a. server address provided by the Azure Iot Hub service.
Message Type	GSM values MQTT messages; default: GSM values	Values that are to be sent to the Azure server.
MQTT Host	ip host; default: none	IP address or hostname of an MQTT broker.
MQTT Port	integer [0..65535]; default: none	Port number of an MQTT broker.
MQTT Host Topic	ip host; default: none	.
Username/Password	string; default: none	MQTT topic to subscribe to. Username and password used for authentication to n MQTT broker.

Cumulocity

Cumulocity is a cloud-based, real-time IoT management platform compatible with Teltonika-Networks devices.

The figure and table below provide explanations for Cumulocity configuration parameters available on the device. For a detailed configuration guide, [click here](#).



Field	Value	Description
Enable	yes no; default: no	Turns the Cumulocity service on or off.
Use SSL/TLS	yes no; default: no	Turn SSL/TLS protocol support on or off.
Server Address	ip host; default: none	Hostname of your Cumulocity server. It should match the <i>Environment name</i> from the Cumulocity registration. For example: <i>teltonika-networks.eu-latest.cumulocity.com</i>
Interval	integer; default: none	Connection push interval in minutes. This field defines how often the device will try to connect to the Cumulocity server.
Reset Auth	- (interactive button)	Resets authentication for this device. If you click this, you'll have to authorize this from Cumulocity dashboard before it can successfully connect to the server again.

Cloud of Things

The **Cloud of Things** is an IoT cloud platform which provides the possibility to remotely monitor, manage and control your connected devices and machines – plug-and-play, without extensive installation.



Field	Value	Description
Enable	yes no; default: no	Turns the Cloud of Things service on or off.
Server Address	ip host; default: none	Hostname of your Cloud of Things server.
Interval	integer; default: none	Push connection interval in minutes.
Reset Auth	- (interactive button)	Resets authentication data so that device could be re-registered on the Cloud of Things Device Management platform.

ThingWorx

The **ThingWorx** platform is used for remote device management and monitoring in the form of user configured custom "things" and applications.

The figure and table below provide explanations for ThingWorx configuration parameters available on the device. For a detailed configuration guide, [click here](#).



Field	Value	Description
Enable	yes no; default: no	Turns the ThingWorx service on or off.
Server Address	ip host; default: none	Hostname of your ThingWorx server.
Server Port	integer [0..65535]; default: none	Port number of your ThingWorx server.
Thing Name	string; default: none	Thing name defined in ThingWorx CP.
Application Key	string; default: none	Application key generated in ThingWorx CP.

[[Category:{{{name}}} Services section (legacy)]]