

TRB160 Powering Options

[Main Page](#) > [TRB Gateways](#) > [TRB160](#) > [TRB160 Manual](#) > **TRB160 Powering Options**

This chapter contains information on **powering options** supported by TRB160 devices.

□

Contents

- [1 Power socket](#)
- [2 Power over Type-c](#)
- [3 Passive PoE](#)
 - [3.1 Simultaneous powering](#)
- [4 Ground loops](#)

Power socket

The TRB160 device can be powered over the 4 pin connector using a 9-30 VDC power supply unit (PSU). Refer to the image below for the power socket pinout information:

✘

If you decide not to use the standard 9 VDC PSU and want to power the device from a higher voltage, please make sure that you choose a power supply of high quality. Some power supplies can produce voltage peaks significantly higher than the declared output voltage, especially during connection and disconnection.

While the device is designed to accept input voltage in the range of 9-30 VDC, high voltage power supplies can harm the device. If you want to use high voltage power supplies it is recommended to also use additional safety equipment to suppress voltage peaks from the power supply.

Power over Type-c

The device may also be powered via the USB Type-C Connector (USB3.0). It supports **5VDC** voltage:

✘

Passive PoE

The device may also be powered via the Ethernet port:

✘

- The device is **NOT COMPLIANT** with the IEEE 802.3af-2003 standard: powering the device from an IEEE 802.3af-2003 power supply **will damage the device** as it is not rated for input voltages of the PoE standard.

- The device is **NOT COMPLIANT** with the IEEE 802.3at standard: it cannot power other devices over Ethernet.

RJ45 pinout:

10/100 Pin mode B, DC on spares		T568A Color	T568B Color	Pins on plug face (socket is reversed)
1	TX+	<input type="checkbox"/> white/green stripe	<input type="checkbox"/> white/orange stripe	
2	TX-	<input type="checkbox"/> green solid	<input type="checkbox"/> orange solid	
3	RX+	<input type="checkbox"/> white/orange stripe	<input type="checkbox"/> white/green stripe	
4	DC+ 9-30 VDC	<input type="checkbox"/> blue solid	<input type="checkbox"/> blue solid	
5	DC+ 9-30 VDC	<input type="checkbox"/> white/blue stripe	<input type="checkbox"/> white/blue stripe	
6	RX-	<input type="checkbox"/> orange solid	<input type="checkbox"/> green solid	
7	DC-	<input type="checkbox"/> white/brown stripe	<input type="checkbox"/> white/brown stripe	
8	DC-	<input type="checkbox"/> brown solid	<input type="checkbox"/> brown solid	

Simultaneous powering

The device can be powered from the power socket and over Ethernet simultaneously.

The power socket has higher priority meaning that the device will draw power from the power socket as long as it is available. When the device is switching from one power source to another it loses power for a fraction of a second and may reboot. The device will function correctly after the reboot.

Ground loops

Do not connect the power supply negative terminal of our device to the chassis or earth exclusively.

This connection could cause ground loops. For example, if the antenna shield and power supply negative terminal are connected to the chassis or earth, it forms a ground loop, therefore unwanted current could flow through a device PCB ground and may cause damage.

