

TSW210 Powering Options

[Main Page](#) > [TSW Switches](#) > [TSW210](#) > [TSW210 Manual](#) > **TSW210 Powering Options**

This chapter contains information on powering options supported by TSW210 switch.

□

Contents

- [1 Power socket](#)
 - [1.1 2 pin power socket](#)
- [2 Ground loops](#)

The switch has a 2 pin power socket and can be powered by a 7-57 VDC power supply unit (PSU). Refer to the image below for the power socket's pinout information:

Power socket

2 pin power socket

No.	Description	Wire color	
1	Power	Red	
2	Ground	Black	

If you decide not to use the standard 50 VDC power supply unit and want to power the device with other voltages (7-57 VDC), please make sure that you choose a power supply of high quality. Some power supplies can produce voltage peaks significantly higher than the declared output voltage, especially during connection and disconnection.

While the device is designed to accept input voltage of up to 57 VDC peaks, high voltage power supplies can harm the device. If you want to use high voltage power supplies it is recommended to also use additional safety equipment to suppress voltage peaks from the power supply.

Ground loops

Do not connect the power supply negative terminal of our device to the chassis or earth exclusively.

This connection could cause ground loops. For example, if the antenna shield and power supply negative terminal are connected to the chassis or earth, it forms a ground loop, therefore unwanted current could flow through a device PCB ground and may cause damage.

In networking switches connecting our device power supply negative terminal to the chassis or earth could cause damage to other devices connected to the switch or unintentional power up of other devices.

