

# RUT906 Powering Options

[Main Page](#) > [RUT Routers](#) > [RUT906](#) > [RUT906 Manual](#) > **RUT906 Powering Options**

This chapter contains information on **powering options** supported by RUT906 routers.

□


## Contents

- [1 Power socket](#)
- [2 Passive PoE](#)
- [3 Simultaneous powering](#)

## Power socket

The router has a 4 pin power socket and can be powered by a **9-30 VDC** power supply unit (PSU). Refer to the image below for the power socket's pinout information:

### Power socket pinout

| No. | Description | Wire color  |
|-----|-------------|---|
| 1   | Power       | Red  |
| 2   | Ground      | Black   |
| 3   | Input       | Green   |
| 4   | Output      | White   |

If you decide not to use the standard 9 VDC wall adapter and want to power the device from a higher voltage (15-30 VDC), please make sure that you choose a power supply of high quality. Some power supplies can produce voltage peaks significantly higher than the declared output voltage, especially during connection and disconnection.

While the device is designed to accept input voltage of up to 30 VDC peaks, high voltage power supplies can harm the device. If you want to use high voltage power supplies it is recommended to also use additional safety equipment to suppress voltage peaks from the power supply.

## Passive PoE

The device may also be powered by an Ethernet cable via the **LAN1** port:  
**(Do not use in other ports!)**



- The device is **NOT COMPLIANT** with the IEEE 802.3af-2003 standard: powering the device from an IEEE 802.3af-2003 power supply **will damage the device** as it is not rated for input voltages of the PoE standard.

- The device is **NOT COMPLIANT** with the IEEE 802.3at standard: it cannot power other devices over Ethernet.
- The device is **NOT COMPLIANT** with the IEEE 802.3bt standard.

**RJ45 pinout:**

| <b>10/100</b>                   |              | <b>T568A Color</b>                           |  | <b>T568B Color</b> |  | <b>Pins on plug face (socket is reversed)</b> |
|---------------------------------|--------------|--|--|--------------------|--|---|
| <b>Pin mode B, DC on spares</b> |              |  |  |                    |  |   |
| 1                               | TX+          | <input type="checkbox"/> white/green stripe  | <input type="checkbox"/> white/orange stripe |                    |  |   |
| 2                               | TX-          | <input type="checkbox"/> green solid         | <input type="checkbox"/> orange solid        |                    |  |   |
| 3                               | RX+          | <input type="checkbox"/> white/orange stripe | <input type="checkbox"/> white/green stripe  |                    |  |   |
| 4                               | DC+ 9-30 VDC | <input type="checkbox"/> blue solid          | <input type="checkbox"/> blue solid          |                    |  | <input type="checkbox"/>                      |
| 5                               | DC+ 9-30 VDC | <input type="checkbox"/> white/blue stripe   | <input type="checkbox"/> white/blue stripe   |                    |  |   |
| 6                               | RX-          | <input type="checkbox"/> orange solid        | <input type="checkbox"/> green solid         |                    |  |   |
| 7                               | DC-          | <input type="checkbox"/> white/brown stripe  | <input type="checkbox"/> white/brown stripe  |                    |  |   |
| 8                               | DC-          | <input type="checkbox"/> brown solid         | <input type="checkbox"/> brown solid         |                    |  |   |

## Simultaneous powering

The router can be powered from a power socket and over Ethernet simultaneously. **In this case, both PSUs should have similar output voltages.** The power socket has higher priority meaning that the device will draw power from the power socket as long as it is available.

When the device is switching from one power source to another it loses power for a fraction of a second and may reboot. The device will function correctly after the reboot.