

RUT951 Powering Options

[Main Page](#) > [RUT Routers](#) > [RUT951](#) > [RUT951 Manual](#) > **RUT951 Powering Options**

This chapter contains information on **powering options** supported by RUT951 routers.

□


Contents

- [1 Power socket](#)
- [2 Passive PoE](#)
- [3 Simultaneous powering](#)
- [4 Ground loops](#)

Power socket

The router has a 4 pin power socket and can be powered by a **9-30 VDC** power supply unit (PSU). Refer to the image below for the power socket's pinout information:

Power socket pinout

No.	Description	Wire color	
1	Power	Red	
2	Ground	Black	
3	Input	Green	
4	Output	White	

If you decide not to use the standard 9 VDC wall adapter and want to power the device from a higher voltage (15-30 VDC), please make sure that you choose a power supply of high quality. Some power supplies can produce voltage peaks significantly higher than the declared output voltage, especially during connection and disconnection.

While the device is designed to accept input voltage of up to 30 VDC peaks, high voltage power supplies can harm the device. If you want to use high voltage power supplies it is recommended to also use additional safety equipment to suppress voltage peaks from the power supply.

Passive PoE

The device may also be powered by an Ethernet cable via the **LAN1** port:
(Do not use in other ports!)




- The device is **NOT COMPLIANT** with the IEEE 802.3af-2003 standard: powering the device from an IEEE 802.3af-2003 power supply **will damage the device** as it is not rated for input

voltages of the PoE standard.

- The device is **NOT COMPLIANT** with the IEEE 802.3at standard: it cannot power other devices over Ethernet.
- The device is **NOT COMPLIANT** with the IEEE 802.3bt standard.

RJ45 pinout:

10/100		RJ45 pinout:		
Pin mode B, DC on spares	T568A Color	T568B Color	Pins on plug face (socket is reversed)	
1	TX+ white/green stripe	white/orange stripe		
2	TX- green solid	orange solid		
3	RX+ white/orange stripe	white/green stripe		
4	DC+ 9-30 VDC blue solid	blue solid		
5	DC+ 9-30 VDC white/blue stripe	white/blue stripe		
6	RX- orange solid	green solid		
7	DC- white/brown stripe	white/brown stripe		
8	DC- brown solid	brown solid		



The diagram shows a grey rectangular area representing the plug face of an RJ45 socket. A small red 'x' icon is positioned on the left side, corresponding to pin 5 in the table above, indicating that the pinout for this pin is reversed in the socket.

Simultaneous powering

The router can be powered from a power socket and over Ethernet simultaneously. **In this case, both PSUs should have similar output voltages.** The power socket has higher priority meaning that the device will draw power from the power socket as long as it is available.

When the device is switching from one power source to another it loses power for a fraction of a second and may reboot. The device will function correctly after the reboot.

Ground loops

Do not connect the power supply negative terminal of our device to the chassis or earth exclusively.

This connection could cause ground loops. For example, if the antenna shield and power supply negative terminal are connected to the chassis or earth, it forms a ground loop, therefore unwanted current could flow through a device PCB ground and may cause damage.

