RUTX14 Powering Options

<u>Main Page</u> > <u>RUTX Routers</u> > <u>RUTX14</u> > <u>RUTX14 Manual</u> > **RUTX14 Powering Options**

This chapter contains information on **powering options** supported by RUTX14 routers.

Contents

- 1 Power socket
- 2 Passive PoE

Power socket

The router has a 4 pin power socket and can be powered by a **9-50 VDC** power supply unit (PSU). Refer to the image below for the power socket's pinout information:

Power socket pinout

×

If you decide not to use the standard 9 VDC wall adapter and want to power the device from a higher voltage (15-50 VDC), please make sure that you choose a power supply of high quality. Some power supplies can produce voltage peaks significantly higher than the declared output voltage, especially during connection and disconnection.

While the device is designed to accept input voltage of up to 50 VDC peaks, high voltage power supplies can harm the device. If you want to use high voltage power supplies it is recommended to also use additional safety equipment to suppress voltage peaks from the power supply.

Passive PoE

The device may also be powered by an Ethernet cable via the **LAN1** port: **(Do not use in other ports!)**



- The device is **NOT COMPLIANT** with the IEEE 802.3af-2003 standard: powering the device from an IEEE 802.3af-2003 power supply **will damage the device** as it is not rated for input voltages of the PoE standard.
- The device is NOT COMPLIANT with the IEEE 802.3at standard: it cannot power other

devices over Ethernet.

RJ45 pinout:

	1910 p						
10/100 Pin mode B, DC on spares			T568A Color	T568B Color	Pins on plug face (socket is reversed)		
1		TX+	white/green stripe	white/orange stripe			
2		TX-	green solid	x orange solid			
3		RX+	white/orange stripe	≭ white/green stripe			
4	DC+	9-50 VDC	blue solid	blue solid			
5	DC+	9-50 VDC	white/blue stripe	white/blue stripe	×		
6		RX-	orange solid	green solid			
7	DC-		white/brown stripe	white/brown stripe			
8	DC-		brown solid	brown solid			