

# Template:Networking device manual unmanaged switch recovery troubleshooting



## Contents

- [1 Summary](#)
- [2 Ethernet port LEDs not lighting up](#)
- [3 Connected devices have no internet](#)
- [4 Connected device not powered via PoE](#)
- [5 RMA](#)

## Summary

{{{name}}} is an unmanaged switch without active operating system running to control inside processes. All work is done by integrated chips, which has built-in logic to control switching and PoE operations.

This chapter contains information of possible **recovery and troubleshooting** options for a {{{name}}} unmanaged switch.

## Ethernet port LEDs not lighting up

### I. Issue

{{{name}}} **green** Ethernet port LED is not lighting up (**orange** LED lit)

#### Solution

{{{name}}} switch **green** Ethernet port LED indicates Gigabit connection with device. Check if connected device network card supports Gigabit speeds or software configuration is not limited to 10/100 Mbps.

### II. Issue

{{{name}}} is not powered up

#### Solution

Check the front panel [power LED](#) if it is lit. If not, try to use other 7-57 VDC power supply, which can provide at least 2 W of power. More information about {{{name}}} powering options check [here](#)

### III. Issue

Connected device is not powered up

#### Solution

Check if connected device is powered up and working properly

#### IV. Issue

Bad cabling between {{{name}}} and connected device

#### Solution

Use other Ethernet cable to connect {{{name}}} with device

#### V. Issue

Defected {{{name}}} Ethernet port

#### Solution

Use other free {{{name}}} Ethernet port to connect switch with device. If device establishes connection with {{{name}}} using other Ethernet port, {{{name}}} is defective and must be sent for service inspection and repairs. Check [{{{name}}}\_Device\_Recovery\_and\_Troubleshooting\_Options#RMA | RMA] section for further instructions

#### VI. Issue

Defected {{{name}}} switch

#### Solution

If {{{name}}} Ethernet port LED are not lighting up after doing above mentioned actions, {{{name}}} is defective and must be sent for service inspection and repairs. Check [{{{name}}}\_Device\_Recovery\_and\_Troubleshooting\_Options#RMA | RMA] section for further instructions

## Connected devices have no internet

#### I. Issue

Connected router/modem do not have internet connection

#### Solution

Check connected router/modem users manual how to diagnose and troubleshoot internet connection issue

#### II. Issue

Bad cabling between {{{name}}} and router/modem

#### Solution

Check cabling from {{{name}}} to router/modem. If link between devices is established, orange LED at connected Ethernet port must be lit ([LEDs meaning](#)). If LED has not lit, change Ethernet cable, connect other router/modem and check again

#### III. Issue

Bad cabling between {{{name}}} and connected device

**Solution**

Check cabling from {{{name}}} to connected device. If link between devices was established, **orange** LED at connected Ethernet port must be lit ([LEDs meaning](#)). If LED has not lit, change Ethernet cable and check again

**IV. Issue**

Defected {{{name}}} switch

**Solution**

Connect device directly to router/modem and check if internet connection was established. If device gets access to internet, when directly connected to router/modem. Try turn switch off and on (restart), if issue persists, {{{name}}} is defective and must be sent for service inspection and repairs. Check [\[\[{{{name}}}\\_Device\\_Recovery\\_and\\_Troubleshooting\\_Options#RMA | RMA\]\]](#) section for further instructions

## Connected device not powered via PoE

**I. Issue**

Connected device to {{{name}}} is not powered via PoE

**Solution I**

Check if connected device supports 802.3af and/or 802.3at PoE standard(s)

**Solution II**

Check if {{{name}}} is powered with PSU, which outputs 44 VDC or higher voltages and can provide at least 2 W + connected device needed power

**II. Issue**

All PoE devices and switch lost power after connecting more than two device to {{{name}}}

**Solution**

{{{name}}} supports 802.3at standard, where each port can supply up to 30 W of power at PSE with total power budget of 120 W per all 4 ports. Standard PSU, which comes in the box with {{{name}}}, provides ~65 W power and limits power budget to ~60 W. If all connected devices to PoE ports combined required more than 60 W of power, PSU was overloaded and turned itself off.

If full 120 W power budget is necessary, {{{name}}} must be powered with PSU, which can provide at least 130 W power at 44 VDC or higher voltages

## RMA

If conventional recovery methods do not help, you may need to send the device to warranty for repair. The warranty process is described [here](#).

[[Category:{{{name}}} Manual]]