RUTXR1 Power Consumption

 $\underline{\text{Main Page}} > \underline{\text{RUTX Routers}} > \underline{\text{RUTXR1}} > \underline{\text{RUTXR1 Manual}} > \underline{\text{RUTXR1 Power Consumption}}$

Averaged <u>RUTXR1</u> power consumption values in different states of operation are represented in the tables below:

Idle, no SIM card inserted (9 V) Idle, no SIM card inserted (12 V) Idle, no SIM card inserted (24 V)	Test type	Current (mA) 441 330 174	Power consumption (W) 3.97 3.96 4.18
Idle + mobile data on ¹ (9 V) Idle + mobile data on ¹ (12 V) Idle + mobile data on ¹ (24 V)	Test type	Current (mA) 447 334 175	Power consumption (W) 4.02 4.01 4.20
Mobile data on ¹ + 1 LAN device connected ² (9 V) Mobile data on ¹ + 1 LAN device connected ² (12 V) Mobile data on ¹ + 1 LAN device connected ² (24 V)	Test type	Current (mA) 515 390 196	Power consumption (W) 4.64 4.68 4.70
Test type Max speed LTE transmission + 5 LAN devices connected ² + high CPU load ³ + data transfer via WiFi +		Current (mA)	Power consumption (W)
USB device connected ⁴ (9 V) Max speed LTE transmission + 5 LAN devices connected ² + high CPU load ³ + data transfer via WiFi +		1235 9.24	11.12 11.09
USB device connected ⁴ (12 V) Max speed LTE transmission + 5 LAN devices connected ² + high CPU load ³ + data transfer via WiFi + USB device connected ⁴ (24 V)		464	11.14

¹ - Only mobile data connection established with no additional traffic.

Power consumption may differ due to mobile data transmission speed, testing environment and conditions.

² - Data streams between RUTXR1 and other connected LAN devices created using iPerf.

 $^{^{3}}$ - Load created using md5sum (calculation and verification of 128-bit MD5 hashes).

 $^{^{4}}$ - USB device with ~ 500 mA current draw.