

Template:Networking rut2xx manual modbus modbus tcp set parameters table

value to set	register address	register number	register value	description
Hostname	7	8	Hostname	Changes hostname
Device name	71	72	Device name	Changes device name
Switch WiFi (ON/OFF*)	203	204	1 0	Turns WiFi ON or OFF
Switch mobile data connection (ON/OFF*)	204	205	1 0	Turns mobile data connection ON or OFF
Reboot	206	207	1	Reboots the router
Change APN	207	208	APN code	Changes APN. The number of input registers may vary depending on the length of the APN, but the very first byte of the set APN command has to be specified as 1
Switch PIN4 state (ON/OFF*)	325	326	1 0	Turns PIN4 state ON or OFF