

Template:Networking rut360 manual supported frequency bands table

-->

Product code	Region (operator)	Supported bands
RUT360 0 *****	Europe ² , the Middle East, Africa, Australia, APAC ³ , Brazil, Malaysia	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz), B32¹ (1500 MHz)• 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz)• 3G: B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
RUT360 1 *****	North America	<ul style="list-style-type: none">• 4G (LTE-FDD): B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B12 (700 MHz), B13 (700 MHz), B25 (1900 MHz), B26 (850 MHz), B29¹ (700 MHz), B30 (2300 MHz), B66 (1700/2100 MHz)• 3G: B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz)

¹ LTE-FDD B29 and B32 support receiving only, and are only for secondary component carrier in 2×CA

² Regional availability - excluding Russia & Belarus.

³ Excluding Japan and CMCC