

# Template:Networking rut360 manual supported frequency bands table

-->

Product code	Region (operator)	Supported bands
RUT360 <b>0</b> *****	Europe <sup>2</sup> , the Middle East, Africa, Australia, APAC <sup>3</sup> , Brazil, Malaysia	<ul style="list-style-type: none"><li>• <b>4G (LTE-FDD)</b>: B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz), B32<sup>1</sup> (1500 MHz)</li><li>• <b>4G (LTE-TDD)</b>: B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz)</li><li>• <b>3G</b>: B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)</li></ul>
RUT360 <b>1</b> *****	North America	<ul style="list-style-type: none"><li>• <b>4G (LTE-FDD)</b>: B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B12 (700 MHz), B13 (700 MHz), B25 (1900 MHz), B26 (850 MHz), B29<sup>1</sup> (700 MHz), B30 (2300 MHz), B66 (1700/2100 MHz)</li><li>• <b>3G</b>: B2 (1900 MHz), B4 (1700 MHz), B5 (850 MHz)</li></ul>

<sup>1</sup> LTE-FDD B29 and B32 support receiving only, and are only for secondary component carrier in 2×CA

<sup>2</sup> Regional availability - excluding Russia & Belarus.

<sup>3</sup> Excluding Japan and CMCC