$https://wiki.teltonika-networks.com/view/Template:Networking\_rut850\_faq\_power\_consumption\_table_e$ 

## Template:Networking rut850 faq power consumption table

<b>Test type</b> No SIM card inserted + GPS turned off + no device connected via WiFi + LED indication turned off (9 V) No SIM card inserted + GPS turned off + no device connected via WiFi + LED indication turned off (12 V) No SIM card inserted + GPS turned off + no device connected via WiFi + LED indication turned off (24 V)	Current (mA) 113 106 53	Power consumption (W) 1.20 1.27 1.27
<b>Test type</b> Mobile data on <sup>1</sup> + GPS on + no device connected via WiFi + LED indication turned off (9 V) Mobile data on <sup>1</sup> + GPS on + no device connected via WiFi + LED indication turned off (12 V) Mobile data on <sup>1</sup> + GPS on + no device connected via WiFi + LED indication turned off (24 V)	Current (mA) 210 159 81	Power consumption (W) 1.89 1.91 1.94
Test type Sleep mode (9 V) Sleep mode (12 V) Sleep mode (24 V)	Current (mA) 21 16 9	Power consumption (W) 0.19 0.19 0.22
<b>Test type</b> GPS on + 1 device connected via WiFi + max speed LTE transmission + LED indication turned on (9 V) GPS on + 1 device connected via WiFi + max speed LTE transmission + LED indication turned on (12 V) GPS on + 1 device connected via WiFi + max speed LTE transmission + LED indication turned on (24 V)	Current (mA) 740 570 288	Power consumption (W) 6.67 6.84 6.91

<sup>1</sup> - Only mobile data connection established with no additional traffic.

Power consumption may differ due to mobile data transmission speed, testing environment and conditions.