

# RUT850 Powering Options

[Main Page](#) > [RUT Routers](#) > [RUT850](#) > [RUT850 Manual](#) > **RUT850 Powering Options**

This chapter contains information on **powering options** supported by RUT850 routers.

□

## Contents

- [1 Power socket](#)

## Power socket

The router has a 4 pin power socket and can be powered by a **9-30 VDC** power supply unit (PSU). Refer to the image below for the power socket's pinout information:

### Power socket pinout

No.	Description	Wire color
1	Not connected	White
2	Ignition	Green
3	Ground	Black
4	Power	Red



If you decide not to use the standard 9 VDC wall adapter and want to power the device from a higher voltage (15-30 VDC), please make sure that you choose a power supply of high quality. Some power supplies can produce voltage peaks significantly higher than the declared output voltage, especially during connection and disconnection.

While the device is designed to accept input voltage of up to 30 VDC peaks, high voltage power supplies can harm the device. If you want to use high voltage power supplies it is recommended to also use additional safety equipment to suppress voltage peaks from the power supply.